



- Check power is on i.e. :
 - (1) RED power switch is in the ON position; and
 - (2) printer LED is on; and
 - (3) Batch Controller display is on.
- Display must show SET and RDY (4) before you can batch.
 - If display shows SET and REC, then press RESET (5).
- use the number kepad to enter the quantity to be batched.
- press SET (6) to lock in the quantity.
- press START BATCH (7) to start batching.
- during Batching:
 - the display shows SET and RUN, and the RUN line counts up.
 - the LEDs will light up:
 - RUN = the pump is being commanded to pump.
 - FLOW = liquid flow is being measured.
 - OUTPUT = not applicable for this installation.

then either

- When batch is complete:
 - the display shows SET and REC; and
 - the RUN, FLOW and OUTPUT LEDs will go out; and
 - two copies of the Batch Ticket will be printed (8).
 - press RESET (5). The display will then show SET and RDY and the unit is ready to batch again.

or

- To terminate the batch before it reaches the set quantity:
 - press STOP (9).
 - wait a 10 seconds.
 - press RESET (5).
 - two copies of the Batch Ticket will be printed (8).

If an alarm occurs during a batch:

- press CANCEL (10), to cancel the alarm; then
- press RESET (5) to terminate the batch.

TMP_short_instruct.doc 1408/1